

BX-32ZW Outdoor Bell Box

High Quality Bell Box with Effective Visual and Audible Alerts



- Siren output level is 107dB at 1 meter
- Elegant, modern design
- Wireless, lightweight, easy to install

BX-32ZW bell box is a battery-operated wireless outdoor siren generating a loud 107 decible siren sound and strobe lights during an alarm to provide visible and audible alerts. The BX-32ZW is energy saving and environmentally conscious, requiring only two Alkaline batteries, yet still has a long battery life of up to four years.

The BX-32ZW generates unique alarm sounds for fire and burglary to inform users of the type of danger at hand. It provides programmable siren duration of 3, 5, and 10 minutes. In addition to producing audible and visible warnings in the case of emergency, the BX-32ZW emits beep notifications for arming and disarming of a security system, and of its low battery status. BX-32ZW also transmits supervisory and low battery signals to the control panel to ensure its faultless operation.

Encased in a durable, IPX5 waterproof elegant design, easy-to-install BX-32ZW is a premium choice for the modern smart home. It's tamper-deterrent feature protects against unauthorized removal and sabotage. The BX-32ZW is compatible with any Z-Wave system and devices.

Features

- Siren output level is 107dB at 1 meter
- Unique alarm sounds for fire and burglary
- Battery life up to 4 years
- · Lightweight and flexible to install
- Smaller, visually pleasing design
- Programmable siren duration of 3/5/10 minutes
- Sound notifications of arming, disarming, and low battery status

- Regular supervision signals to check system integrity and trouble shooting
- · Low battery detection
- Cover tamper protection prevents unauthorized removal and sabotage
- · IPX5 waterproof and UV resistant housing
- · Compliant with CE requirement
- Compatible with any Z-Wave mesh networks and devices

Specifications

Communication Protocol	Z-Wave
Frequency	868.42 MHz (EU)/908.42 MHz (US)
Power Source	3V, D Alkaline batteries x 2
Battery Life*	Up to 4 years
Siren Output	107dB at 1 meter
Operating Temperature	-10°C to 50°C
Operating Humidity	Up to 85% non-condensing
Dimensions	212.5mm x 179mm x 53mm

*Note: Actual battery life may vary with product settings, usage patterns and operating environment.

